

ICP DAS
IoTstar 2025
"Bot Service (LINE)"
Function Manual
[Version 1.0.0 - 2025/02/03]



泓格科技
ICP DAS CO., LTD.

Warning

The information furnished by ICP DAS Co. Ltd. (hereinafter "ICP DAS") is accurate and reliable to ICP DAS's best knowledge. ICP DAS reserves the right to change the content of this manual at any time without notice.

Through the communication mechanisms provided by LINE company, this controller can send the notification messages and information regarding this controller to the related personal account. However, this function may not be available due to LINE company closes or terminates the communication mechanisms of their systems.

ICP DAS cannot guarantee that this controller is free of any actual or legal defects (including but not limited to stability, reliability, accuracy, completeness, validity, suitability for a specific purpose, security related defects, errors or bugs, infringement of rights etc.). ICP DAS shall not be responsible for any damages inflicted upon users in relation to the use of the controller.

Copyright and Trademark Information

© Copyright 2025 by ICP DAS Inc., LTD. All rights reserved worldwide.

Trademark of Other Companies

The names used for identification only maybe registered trademarks of their respective companies.

License

The user can use, modify and backup this software on a single machine. The user may not reproduce, transfer or distribute this software, or any copy, in whole or in part.

Table of Contents

1	Introduction.....	6
2	Before Installation.....	9
2.1	Precondition.....	9
2.2	Software Requirements	10
2.3	The application and setting of LINE account.....	10
2.3.1	Create a LINE Official Account.....	10
2.3.2	The setting of Messaging API.....	13
2.3.3	Change the plan of LINE official accounts.....	17
2.4	Enable IoTstar Bot Service (LINE)	18
2.4.1	The setting of Bot Service (LINE) and Webhook.....	19
2.5	Import SSL certificate.....	22
2.6	Verify the operation of Bot Service (LINE)	24
2.7	Message sending setting from WISE/PMC/PMD to Bot Service (LINE).....	25
2.7.1	The settings of text message sending by WISE-523x/WISE-224x	25
2.7.2	The settings of image or video message sending by WISE-523x/WISE-224x	28
2.7.3	The settings of text message sending by PMC-523x/PMC-224x/ PMD.....	30
2.8	Real-time data sending setting form WISE/PMC/PMD	33
2.8.1	Real-time data sending setting by WISE-523x/WISE-224x 33	
2.8.2	Real-time data sending setting by PMC-523x/PMC-224x/PMD.....	34
3	The Interface and Feature of Bot Service (LINE).....	35
3.1	Join Bot Service for LINE account and enable the linkage	35
3.2	Bot Service (LINE) chat room interface.....	37
3.3	The function of Channel and Group.....	38
3.4	The function of Event Notification	41
3.5	The function of Event.....	42
3.6	The function of Help.....	43
	Appendix I : Apply free SSL from "Let's Encrypt"	45

List of Figures

Figure 1-1: System Architecture of IoTstar 2025	7
Figure 1-2: IoTstar 2025 Bot Service (LINE) System Architecture	8
Figure 2-1: Login the LINE Business ID	11
Figure 2-2: Create a LINE official account page	12
Figure 2-3: LINE Official Account Website - Account List.....	12
Figure 2-4: LINE Official Account Website - Response settings.....	12
Figure 2-5: LINE Official Account Website – Enable Messaging API (1)	13
Figure 2-6: LINE Official Account Website – Enable Messaging API (2)	13
Figure 2-7: LINE Official Account Website – Home Page	14
Figure 2-8: LINE Developer Website - Enter the Messaging API channel	14
Figure 2-9: LINE Developer Website – Get the Channel ID and Secret.....	15
Figure 2-10: LINE Developer Website – Get QR code URL	16
Figure 2-11: LINE Developer Website - Get the Channel access token.....	16
Figure 2-12: LINE Official Account Manager page	17
Figure 2-13: LINE Official Account Manager page - Monthly Plan	18
Figure 2-14: The settings to enable IoTstar Bot Service (LINE) (1)	19
Figure 2-15: The settings to enable IoTstar Bot Service (LINE) (2)	20
Figure 2-16: The settings to enable IoTstar Bot Service (LINE) (3)	20
Figure 2-17: The settings to enable IoTstar Bot Service (LINE) (4)	21
Figure 2-18: The settings to enable IoTstar Bot Service (LINE) (5)	21
Figure 2-19: The settings to enable IoTstar Bot Service (LINE) (6)	22
Figure 2-20: Launch IIS and go into SSL Certificates interface.....	23
Figure 2-21: Import the SSL certificate.....	23
Figure 2-22: Enable the HTTPS connection of the IoTstar website.....	24
Figure 2-23: LINE Developer Website - Verify the operation of Webhook.....	24
Figure 2-24: WISE Web Site - Bot Service Message Setting Page (1)	26
Figure 2-25: WISE Web Site - Bot Service Message Setting Page (2)	26
Figure 2-26: WISE Web Site - Bot Service Message Setting Page (3)	27
Figure 2-27: WISE Web Site - Bot Service Message Setting Page (4)	28
Figure 2-28: WISE Web Site - Rule setting with Bot Service Message	28
Figure 2-29: WISE Web Site - Bot Service Forward Setting Page (1).....	29
Figure 2-30: WISE Web Site - Bot Service Forward Setting Page (2).....	29
Figure 2-31: WISE Web Site - Bot Service Forward Setting Page (3).....	30
Figure 2-32: PMC/PMD Web Site - Bot Service Message Setting Page (1) ..	31

Figure 2-33: PMC/PMD Web Site - Bot Service Message Setting Page (2) ..31
Figure 2-34: PMC/PMD Web Site - Bot Service Message Setting Page (3) ..32
Figure 2-35: PMC/PMD Web Site - Bot Service Message Setting Page (4) ..32
Figure 2-36: PMC/PMD Web Site - Rule setting with Bot Service Message ..33
Figure 2-37: WISE Web Site - Real-time data sending setting34
Figure 2-38: PMC/PMD Web Site - Real-time data sending setting.....34
Figure 3-1: Open the Bot Service (LINE) account QR Code window for
 scanning36
Figure 3-2: Bot Service (LINE) chat room - select the language and the IoTstar
 account36
Figure 3-3: Enable the linkage of IoTstar account and LINE account.....37
Figure 3-4: Bot Service (LINE) chat room - User Interface38
Figure 3-5: Bot Service (LINE) chat room - Controller List.....39
Figure 3-6: Bot Service (LINE) chat room - Group List39
Figure 3-7: Bot Service (LINE) chat room - Channel List.....40
Figure 3-8: Bot Service (LINE) chat room - Group Channel List.....40
Figure 3-9: Bot Service (LINE) chat room - Change Channel Status/Value ...41
Figure 3-10: Bot Service (LINE) chat room - Event Notification42
Figure 3-11: Bot Service (LINE) chat room - Event Browsing Function.....42
Figure 3-12: Bot Service (LINE) chat room - Event List43
Figure 3-13: Bot Service (LINE) chat room - Help Manu.....43
Figure 3-14: Bot Service (LINE) chat room - Channel Sorting Function.....44

1 Introduction

IoTstar 2025 is the latest version of ICP DAS's IoT cloud management software. It integrates the original IoTstar software and service packages (Dashboard Service, Report Service, Bot Service, etc.) into a single product, streamlining IoTstar's purchasing and installation process while making the system more intuitive and convenient to use. In addition to retaining all features and service packages from the previous version, IoTstar 2025 introduces several new user-centric functions and significantly enhances the overall user experience.

IoTstar 2025 can be installed on private PCs or VM (Virtual Machine) systems hosted on cloud platforms such as Microsoft Azure, IBM Bluemix, Amazon AWS and Google Cloud. This enables users to quickly establish their own IoT cloud monitoring systems. With IoTstar 2025, users can create IoT cloud systems that deliver the following services:

1. **Controller Remote Access Service:** Status Monitoring, System Setting, and Firmware Update for WISE/PMC/PMD controllers.
2. **Sensor Data Collection Service:** Collect the data of the sensor connected to the controller and import the data into the Database on cloud.
3. **Sensor Data Visualization Service:** Review the data of the sensor connected to the controller through Dashboard interface.
4. **Sensor Data Report Service:** Provide statistical report for the data of the sensor connected to the controller.
5. **Bot Service with Mobile Phone:** Review the data of the sensor connected to the controller by mobile phone Bot service.



Figure 1-1: System Architecture of IoTstar 2025

IoTstar 2025 Bot Service (LINE) function is an optional software package for IoTstar that provides users a Two-way message interaction between the WISE/PMC/PMD controllers managed by IoTstar and LINE chat rooms. Through IoTstar 2025 Bot Service (LINE) function, the users can query the real-time I/O channel data (or power data) of the I/O module (or power meter) connected to the WISE/PMC/PMD controllers, and instantly change the values of the DO/AO output channels of the I/O modules (or power meters) connected to WISE/PMC/PMD controllers.

In addition, IoTstar 2025 Bot Service (LINE) function can receive the text message sent by the WISE/PMC/PMD controllers through the trigger of IF-THEN-ELSE logic rule and send the text message to the LINE account bound to the LINE chat room for the event notification. If WISE enables the image or video file forwarding function,

IoTstar 2025 Bot Service (LINE) function can also send the photo or video file to the LINE account along with the text message, and user can also review the event list and the corresponding images of controller in the past.




Figure 1-2: IoTstar 2025 Bot Service (LINE) System Architecture

The following chapters will explain the operation of the "Report Service for LINE" function of IoTstar 2025 (hereinafter referred to as IoTstar). For instructions on software installation, system settings and other functions of IoTstar 2025, please refer to the IoTstar 2025 IoT Cloud Management Software User Manual.

2 Before Installation

2.1 Precondition

Before using IoTstar Bot Service (LINE) function, you must first complete the setting of the following preconditions.

- ◆ Complete the installation of IoTstar, and complete the connection setting of IoTstar and WISE/PMC/PMD controllers.
- ◆ The network setting of the computer that installs IoTstar needs to be set as "**Public Network IP**" or "**Dynamic IP + DDNS**", and the user has to apply the **SSL certification** for the IoTstar website.
 - The HTTPS server must use a SSL certificate issued by a certificate authority widely trusted by general web browsers, otherwise LINE will reject to send messages with the web server of IoTstar.
 - "[Appendix I](#)" provides the Step-by-Step document for the application of the free SSL certificate from Let's Encrypt. Before apply the SSL certificate from Let's Encrypt, the IoTstar website must complete the setting of **Domain Name**.
- ◆ Make sure the LINE official account can be applied in the country that IoTstar Bot Service for LINE installed, and make sure the functions of LINE Messaging API can be enabled.
 - The user needs to apply the LINE official account by himself. For the detailed process, please refer to the section "[2.3 The application and setting of the LINE account](#)".
 - The following table provides the information of LINE official account solution, providing free, light and standard options:

	Free	Light	Standard
Monthly Fee	Free	Monthly fee depends on the country in which your account is registered.	
Free Messages	The number of free messages depends on the country in which your account is registered.		
Additional Message Fee	N/A	N/A Only available in Thailand.	Available Message fee depends on the country in which your account is registered.

The introduction websites of LINE account are as below: [Taiwan](#), [Japan](#), [Thailand](#), [Other](#)

- The user can choose the LINE official account solution according to his requirement, and has to pay the fee derived from the selected LINE official account solution to LINE.

2.2 Software Requirements

- ◆ The LINE App on Android or iOS requires version 8.11.0 or later.

2.3 The application and setting of LINE account

Following sections include the topics as below:

- Create a LINE Official Account and enable the Messaging API feature through the LINE Official Account Manager website.
- Complete the settings of the LINE Official Account Manager website and the LINE Developer website.

2.3.1 Create a LINE Official Account

- i Before creating a LINE Official Account, you need to log in to [LINE Business ID](#) using a LINE account or a business account (this LINE account or business account you use to log in the website will have the authority to manage the LINE official account, add users, set up the roles of users, and transfer account).




Figure 2-1: Login the LINE Business ID

- ii After logging into LINE Business ID, you will be directed to [the create a LINE official account page](#). On the page's form, fill in the relevant information for the account you want to create and submit it to complete the creation of the LINE Official Account.

Figure 2-2: Create a LINE official account page

- iii After the LINE Official Account is created, go to [the LINE Official Account Manager website](#) to configure it. In the account list, select the account you just created.




Figure 2-3: LINE Official Account Website - Account List

- iv After entering the selected account, click on "Settings" in the top right corner, then select the "Response settings" tab. Set both "Greeting message" and "Auto-response messages" to "Disabled."




Figure 2-4: LINE Official Account Website - Response settings

- v Select the "Messaging API" tab and click "Enable Messaging API."




Figure 2-5: LINE Official Account Website – Enable Messaging API (1)

vi In the pop-up window, select the provider for this account and click "Agree". The privacy policy and terms of use page can be skipped and do not need to be filled out. Click "OK" to enable the Messaging API feature.




Figure 2-6: LINE Official Account Website – Enable Messaging API (2)

2.3.2 The setting of Messaging API

i After completing the creation of the LINE Official Account and

enabling the Messaging API feature, go to [the LINE Developer website](#) and log in. Click the "Console" button in the top right corner to enter the Console management page.




Figure 2-7: LINE Official Account Website - Home Page

※If you have not logged in on the LINE Developer website before, you will be asked to enter the information of "Name" and "Email address", after that you can start using it. (only on first time login)

- ii In the Providers list on the Console management page, select the provider for the LINE official account you just created, then click on the Messaging API channel for that account.




Figure 2-8: LINE Developer Website - Enter the Messaging API channel

- iii In the "Basic settings" tab of the channel, get the "Channel ID" and

"Channel secret" and make sure to record them.




Figure 2-9: LINE Developer Website – Get the Channel ID and Secret

- iv In the "Messaging API" tab of the channel, click the right mouse button on the "QR code" image, and select "Copy Image Address" to get the "QR code URL" and make sure to record them.




Figure 2-10: LINE Developer Website – Get QR code URL

- v In the "Messaging API" tab of the channel, click the "Issue" button of the "Channel access token (long-lived)" field to generate a token and make sure to record them.



Figure 2-11: LINE Developer Website - Get the Channel access token

- vi Please record "Channel ID", "Channel Secret", "QR Code URL" and "Channel Access Token" information get from the steps above, later you will need these information to enable the functions of IoTstar Bot Service for LINE.

Please note: If you click the "Issue" button again to change the content of "Channel Secret" or "Channel access token" fields, please remember to modify the settings on IoTstar with the new

information.

2.3.3 Change the plan of LINE official accounts

- i Log in to the [LINE Official Account Manager website](#), and in the account list, select the account you want to change the plan.




Figure 2-12: LINE Official Account Manager page

- ii After entering the selected account, click on "Settings" in the top right corner, then select the "Monthly plan" tab. Choose the plan you want to upgrade to, and the plan will be changed. (The plan prices shown in the images are for reference only; actual prices may change.)




Figure 2-13: LINE Official Account Manager page - Monthly Plan

2.4 Enable IoTstar Bot Service (LINE)

To enable the Bot Service (LINE) function on IoTstar, users have to install the IoTstar first. The following sections will introduce the process to enable the Bot Service (LINE) function.

Please note: When enabling the "Bot Service (LINE)" in IoTstar, please ensure that IoTstar is connected to the internet and can maintain a connection to the external network. This will ensure the information transmission between IoTstar and the LINE official server.

2.4.1 The setting of Bot Service (LINE) and Webhook

- i Click "Settings" button on the IoTstar system interface to enter the setting window. Select the tab of "Website" and select https of the "Type" field. If you have modified the IP/Domain Name of IoTstar when create Bot Service, you need to modify the "IP/Domain Name" field.




Figure 2-14: The settings to enable IoTstar Bot Service (LINE) (1)

- ii Select the tab of "Bot Service", check the "Enable" of "Function Status" field in the "LINE" section to enable the function, and enter the information you get from the [2.3.2 The setting of Messaging API](#) section such as "Channel ID", "Channel secret", "Channel

access token" and "QR code URL" in the corresponding fields of "LINE" section.




Figure 2-15: The settings to enable IoTstar Bot Service (LINE) (2)

- iii Click "Copy URL to clipboard" button of "Webhook URL" field to copy the URL of IoTstar.




Figure 2-16: The settings to enable IoTstar Bot Service (LINE) (3)

- iv Go to the Messaging API channel page of [LINE Developer website](#), paste the URL on the "Webhook URL" field by clicking the "Edit" button of the Messaging API tab and click "update" button, and turn on the switch of the "Use Webhook" to enable Webhook..




Figure 2-17: The settings to enable IoTstar Bot Service (LINE) (4)

- v Return to IoTstar system interface. Select the tab of "Miscellaneous", you can set the folder path for controller event video and photo file storage of "Video & Photo Folder" field. Click the "OK" button to complete the settings.




Figure 2-18: The settings to enable IoTstar Bot Service (LINE) (5)

- vi Click "Start Service" to launch IoTstar, then the Bot Service for LINE function will also be enabled at the same time.




Figure 2-19: The settings to enable IoTstar Bot Service (LINE) (6)

2.5 Import SSL certificate

To enable IoTstar Bot Service (LINE), user has to import the SSL certificate into IIS (Internet Information Service). The SSL certificate can be obtained for free or for a fee. So please use the IP or Domain Name of the IoTstar website to obtain its corresponding SSL certificate first, and then perform following steps to import the SSL certificate into IIS, or refer to "[Appendix I](#)" to apply the free SSL certificate of Let's Encrypt and import it into IIS. **Please Note: If user follows the steps of Appendix I, the software will help user to get the SSL certificate, import it to IIS automatically. So please skip the steps in the section 2.5).**

- i Launch "Internet Information Services (IIS) Administrator" and click on the "Server Certificates".




Figure 2-20: Launch IIS and go into SSL Certificates interface

- ii Click the "Import..." on the right side of the "Server Certificates" window. Browse the SSL certificate in the **pxf** file format, enter the password of the certificate, and click the "OK" button to finish the import process.




Figure 2-21: Import the SSL certificate

- iii Select the IoTstar website on the left side of the IIS window, and click on the "Binding..." on the right side of the IIS window, and then select the IP/Host Name setting by the IoTstar. Finally, select the SSL certificate and click the "OK" button.




Figure 2-22: Enable the HTTPS connection of the IoTstar website

2.6 Verify the operation of Bot Service (LINE)

Go back to the Messaging API page created by the [LINE Developer website](#) and click the "Verify" button of the "Webhook URL" field in the Messaging API tab. If the pop-up message displays "Success", it means the operation of IoTstar Bot Service (LINE) is successful.




Figure 2-23: LINE Developer Website - Verify the operation of Webhook

If the operation is not successful, please verify the following items:

- (1) The computer IoTstar installed must be equipped with **"Public Static IP"** or **"Dynamic IP + DDNS"**.
- (2) The IoTstar website must have the SSL certificate, and the HTTPS server must use an SSL certificate issued by a certificate authority widely trusted by general web browsers.
- (3) The content of "Webhook URL" of the "Messaging settings" section of the LINE Developer website must be correct. The format of the setting must be **https://(IoTstar web address)/webhook.php**.
- (4) The "IP/Domain Name" under the "Web" tab of the "Settings" page on the IoTstar system interface must be correct.
- (5) The "Channel ID", "Channel secret", "Channel access token" and "QR code URL" under the "LINE" section of the "Bot Service" tab of the "Settings" page on the IoTstar system interface must be correct.
- (6) Check if the Service of IoTstar has been started.

2.7 Message sending setting from WISE/PMC/PMD to Bot Service (LINE)

The user can edit the WISE/PMC/PMD's IF-THEN-ELSE logic rule setting to trigger the message sending operation. When WISE/PMC/PMD sends the message, the message will be sent to the corresponding LINE account via IoTstar Bot Service (LINE). The content of message can include the Real-Time I/O channels data, power data or Internal Register data. In addition, WISE also provides image or video data sending function to send the image or video data to the corresponding LINE account.

2.7.1 The settings of text message sending by WISE-523x/WISE-224x

- i Launch a Browser to login into the WISE, and enter the "IoT Platform Setting" Page. Click the "Bot Service Message Setting" button under the "IoTstar Setting" section on the left side of the webpage to enter the "Bot Service Message Setting" page.




Figure 2-24: WISE Web Site - Bot Service Message Setting Page (1)

- ii Click on "Add new Message" to open the "Bot Service Message Setting" Page.




Figure 2-25: WISE Web Site - Bot Service Message Setting Page (2)

- iii Input name in the "Nickname" field, and you could also input the description of this Bot Service message in the "Description" field. Enter the message in the "Content" field. The Bot Service message provides an encoded string for you to add current I/O channel data or Internal Register data into the Bot Service message. To make it easy to add the encoded string, WISE provides "Real-time variable editor" for users. Click on "OK" to confirm the setting and leave the setting page.

The screenshot displays the 'Message Message 1 Setting' interface. It features a form with the following elements:

- *Nickname:** A text input field containing 'Message 1'.
- Description:** An empty text input field.
- *Content:** A large text area for entering the message content. Above this area are 'View' and 'Edit' buttons. Below the text area are configuration options: 'Interface' (XV-Board), 'Module' (XV308), 'Channel' (DI), and 'Ch.' (1), each with a dropdown arrow. An 'Insert' button is located below these options.
- Buttons:** 'OK' and 'Cancel' buttons are positioned at the bottom right of the form.

Figure 2-26: WISE Web Site - Bot Service Message Setting Page (3)

- iv Repeat steps ii~iii to complete the settings of all Bot Service message. After you finish all the Bot Service message settings, click "Save" button to save the settings.




Figure 2-27: WISE Web Site - Bot Service Message Setting Page (4)

- v Go to the "Rule Setting" page and click "Add new rule". The "Rule Setting" page will appear. Click the "Bot Service" option under the THEN/ELSE section, and select the Bot Service message. Now if the evaluation of the "IF statement" is "true", the selected Bot Service message will be sent, and the LINE accounts linked with the IoTstar account who manages this WISE controller will receive the messages in the Bot Service for LINE chat room.




Figure 2-28: WISE Web Site - Rule setting with Bot Service Message

2.7.2 The settings of image or video message sending by WISE-523x/WISE-224x

- i Launch a Browser to login into the WISE, and enter the "IoT Platform Setting" Page. Click the "Video Data Sending Setting" button under the "IoTstar Setting" section on the left side of the webpage to enter the "Video Data Sending Setting" page.




Figure 2-29: WISE Web Site - Bot Service Forward Setting Page (1)

- ii Click the tab on the right-top corner of "Video Data Sending Setting" page. Choose the data source, and click the "Setting" button to enter the setting page.




Figure 2-30: WISE Web Site - Bot Service Forward Setting Page (2)

- iii Check the "Enable" function, and then the message setting interface will be shown as below. Enter the message in the "Content of Attached Message" field. Check "Forward to Bot Service" in the "Bot Service" field. Click on "OK" to confirm the setting and leave the setting page.

IP Camera iCAM-MR6422X(192.168.100.94:80) Video Data Sending Setting

Function Status Enable

*Content of Attached Message

View Edit

From IP Camera

The image will be sent with this message.

Bot Service Forward to Bot Service

OK Cancel

Figure 2-31: WISE Web Site - Bot Service Forward Setting Page (3)

- iv After you finish all the settings, click "Save" button to save the settings. Now if WISE received the image or video data sending from the data source, WISE will send the image or video data with the text message to the Bot Service for LINE chat room.

2.7.3 The settings of text message sending by PMC-523x/PMC-224x/PMD

- i Launch a Browser to login into the PMC/PMD, and enter the "IoT Platform Setting" Page. Click the "Bot Service Message Setting" button under the "IoTstar Setting" section on the left side of the webpage to enter the "Bot Service Message Setting" page.




Figure 2-32: PMC/PMD Web Site - Bot Service Message Setting Page (1)

- ii Click on "Add new Message" to open the "Bot Service Message Setting" Page.




Figure 2-33: PMC/PMD Web Site - Bot Service Message Setting Page (2)

- iii Input name in the "Nickname" field, and you could also input the description of this Bot Service message in the "Description" field. Enter the message in the "Content" field. The Bot Service message provides an encoded string for you to add current I/O channel data, power data or Internal Register data into the Bot Service message. To make it easy to add the encoded string, PMC/PMD provides "Real-time variable editor" for user. Click on "OK" to confirm the setting and leave the setting page.

Message Message 1 Setting

*Nickname:

Description:

*Content:

Interface:

Module:

Channel: Info.

Figure 2-34: PMC/PMD Web Site - Bot Service Message Setting Page (3)

iv Repeat steps ii to iii to complete the settings of all Bot Service message setting. After you finish all the Bot Service message settings, click "Save" button to save the settings.

Bot Service Message Setting Page

Nickname	Content
+ Add new message	
Message 1	PM-4324 Submeter2 Phase A V PM-4324 Submeter4 Phase B V

Figure 2-35: PMC/PMD Web Site - Bot Service Message Setting Page (4)

- v Go to the "Rule Setting" page and click "Add new rule". The "Rule Setting" page will appear. Click the "Bot Service" option under the THEN/ELSE section, and select the Bot Service message, Now if the evaluation of the "IF statement" is "true", the selected Bot Service message will be sent, and the LINE accounts linked with the IoTstar account who manages this WISE controller will receive the messages in the Bot Service for LINE chat room.

The screenshot displays the "Rule Information Setting" and "Rule Content Setting" sections. The "Rule Information Setting" section includes fields for "Nickname" (Rule 1), "Description", and "Status" (Enable/Disable). The "Rule Content Setting" section is divided into three columns: "IF", "THEN", and "ELSE". The "IF" column has a "Set a Condition" dropdown and a "No Condition exists" message. The "THEN" column has a "Set an Action" dropdown with a menu open showing "ICP DAS Module", "Power Meter", "Bot Service" (highlighted with a red box), and "Internal Register". The "ELSE" column has a "Set an Action" dropdown and a "No Action exists" message. "Save" and "Cancel" buttons are at the bottom.

Figure 2-36: PMC/PMD Web Site - Rule setting with Bot Service Message

2.8 Real-time data sending setting form WISE/PMC/PMD

All I/O channel data (or Power data) displayed on IoTstar Bot Service (LINE) are real-time data. Therefore, users need to complete the Real-time Data Sending Setting on the WISE/PMC/PMD controllers to show real-time data on IoTstar Bot Service (LINE).

2.8.1 Real-time data sending setting by WISE-523x/WISE-224x

- i Launch a Browser to login into the WISE, and enter the "IoT Platform Setting" Page.
- ii Click the "Real-time Data Sending Setting" button under the "IoTstar Setting" section on the left side of the webpage to enter the "Real-time Data Sending Setting" page.
- iii Check the "Enable" function, and add channels to be displayed.
- iv After all settings are completed, click "Save" button to save the setting.




Figure 2-37: WISE Web Site - Real-time data sending setting

2.8.2 Real-time data sending setting by PMC-523x/PMC-224x/PMD

- i Launch a Browser to login into the PMC/PMD, and enter the "IoT Platform Setting" Page.
- ii Click the "Real-time Data Sending Setting" button under the "IoTstar Setting" section on the left side of the webpage to enter the "Real-time Data Sending Setting" page.
- iii Check the "Enable" function, and add channels to be displayed.
- iv After all settings are completed, click "Save" button to save the setting.




Figure 2-38: PMC/PMD Web Site - Real-time data sending setting


3 The Interface and Feature of Bot Service (LINE)

After the application and setting of the LINE account as described in the above chapter is completed, users can start the linkage setting between the personal LINE account and the IoTstar account. After the linkage setting completed, the Two-way message communication interaction between WISE/PMC/PMD controllers managed by IoTstar and the LINE account can be performed within the Bot Service (LINE) chat room. Following is the feature IoTstar Bot Service (LINE) provides:

- Monitoring/Control of the I/O channel data (or power data): Review the real-time I/O channel data (or power data) and change the value of the DO/AO channel of the I/O modules (or power meter) connected to WISE/PMC/PMD.
- Monitoring of the grouping data: With the IoTstar's grouping function, can quickly monitor the real-time data of the grouping I/O channels (or power loop).
- Event Notification: The logic rule of Event notification can be set on the WISE/PMC/PMD controller. When the conditions of the IF-THEN-ESLE logic rule are met, the action of "Event message sending" will be triggered to send the message to all linked LINE accounts.
- Review the historical events of controllers: Records the event messages sent by the WISE/PMC/PMD controller and the user can review the content of the event message from the event list, including the message text, images and videos.

The interface and function of IoTstar Bot Service will be described below.

3.1 Join Bot Service for LINE account and enable the linkage

Log in to the IoTstar website, click on "Account Maintenance" button on the "System Information & Setting" section on the IoTstar Webpage; the Account Maintenance Setting page will be displayed as below. Find the "Bot Service for LINE" section, click the  icon on the right side of the "Bot Service for LINE" section to open the QR Code window of the Bot Service account. Use LINE APP to scan the QR Code and add the account.




Figure 3-1: Open the Bot Service (LINE) account QR Code window for scanning

After adding the account, select the language and the IoTstar account to be linked in the LINE chat room.




Figure 3-2: Bot Service (LINE) chat room - select the language and the IoTstar account

Go back to the IoTstar website, enable the LINE accounts in the "Status" field of the "Bot Service for LINE" list to complete the linkage between the LINE account you select and the IoTstar account. Here you can enable/disable/delete the LINE account, and change the account's name.




Figure 3-3: Enable the linkage of IoTstar account and LINE account

3.2 Bot Service (LINE) chat room interface

After completing the account linkage of the IoTstar account and the LINE account, users can see the function buttons in the menu located in the lower area of Bot Service (LINE) chat room. There are four function buttons as Channel, Group, Event and Help, and users can click the button to perform the corresponding function.




Figure 3-4: Bot Service (LINE) chat room - User Interface

3.3 The function of Channel and Group

The messages generated by the channel and group functions will be described as below:




Figure 3-5: Bot Service (LINE) chat room - Controller List




Figure 3-6: Bot Service (LINE) chat room - Group List




Figure 3-7: Bot Service (LINE) chat room - Channel List




Figure 3-8: Bot Service (LINE) chat room - Group Channel List




Figure 3-9: Bot Service (LINE) chat room - Change Channel Status/Value

※To display I/O channel data (or power data) in the list of Channel/Group interfaces as above, users need to follow "[2.8 Real-time data sending setting form WISE/PMC/PMD](#)" section to perform the settings of real-time data sending. Besides, to show I/O channel data (or power data) in Group list, users have to perform the grouping settings on IoTstar webpage: create the group and add real-time channels into it, and then the channels would be shown on the Group list.

3.4 The function of Event Notification

The IF-THEN-ELSE logic rule can be set on WISE/PMC/PMD controller to send a notification message to the corresponding LINE chat room when the event is triggered, and the WISE controller can use the image or video file forwarding function to send the picture or video files at the same time. For more detail, please refer to "[2.7 Message sending setting from WISE/PMC/PMD to IoTstar Bot Service](#)" section.




Figure 3-10: Bot Service (LINE) chat room - Event Notification

3.5 The function of Event

Click "Event" in the menu, the "Event Browsing Function" message will be generated, and the "Search by time" and "The last 10 events" functions will be provided to query the past events.




Figure 3-11: Bot Service (LINE) chat room - Event Browsing Function

The event list is displayed in the units of 10 events each time. If the number of events is greater than 10 events, click the "Next 10 events" button, it will continue to display the next 10 events until the end of the events list.




Figure 3-12: Bot Service (LINE) chat room - Event List

3.6 The function of Help

Click on the "Help" function of the menu, it will help user to review the information of the currently IoTstar account, and provide "Account Setting", "Language Setting" and "Relevant information".




Figure 3-13: Bot Service (LINE) chat room - Help Menu

- **Switch Account:** One LINE account can monitor multiple IoTstar accounts, click to switch to other IoTstar account to monitor the controllers belongs to it.
- **Add a New Account:** One LINE account can monitor multiple IoTstar accounts, click to add a new IoTstar account.

- **Channel Sorting:** If this function was enabled, the channel list would be sorted by the module. Otherwise, it would follow the sequence of the "Real-time data sending setting" on the controller.




Figure 3-14: Bot Service (LINE) chat room - Channel Sorting Function

Appendix I : Apply free SSL from "Let's Encrypt"

[Let's Encrypt](#) is a free, automated and open digital certificate authority service (Certificate Authority; CA) provided by [Internet Security Research Group \(ISRG\)](#). For the detailed information of "How the Let's Encrypt Digital Certificate Authority (CA) performs the issuance/cancellation of the Domain certification and digital certificate", please refer to the [URL link](#).

Let's Encrypt uses the ACME protocol to verify if the Domain is controlled by the user and then will issue the certificate for the Domain if the application is approved. In order to get the certificate, you need to use an ACME Client software. So we suggest you to select an ACME Client software which is suitable for the installed environment of IoTstar from the [recommended list](#). Following we use the win-acme as an example to demonstrate the steps to apply a free SSL certificate from Let's Encrypt:

- (1) Please confirm that IoTstar has been installed successfully and work smoothly, and make sure the IoTstar website has its own Domain Name. If the above 3 conditions are met, then you can issue an application of SSL certificate from Let's Encrypt.

(Before performing the following steps, please confirm that the relevant settings of IIS and the path of the website will not be changed anymore. If the settings of IIS are changed after you completing the following steps, please delete the certificate and re-create a new certificate from step 4 to avoid the failure of automatic certificate update.)

- (2) Download the latest 64 or 32 bit pluggable version of [win-acme](#), create a folder in any directory and unzip the file into this folder (If the directory location is determined, please do not change the location again, it is recommend using C:\Program Files or C:\Program Files (x86)).
- (3) After unzipping the file you download, right click on the wacs.exe, select "execute as system administrator" to launch the file, and perform the following steps to complete the application and creation of SSL certificate:

- A. Select "N: Create new certificate (simple for IIS)" to perform the creation of a new certificate.

```
A simple Windows ACMEv2 client (WACS)
Software version 2.1.6.768 (RELEASE, PLUGGABLE)
ACME server https://acme-v02.api.letsencrypt.org/
IIS version 10.0
Running with administrator credentials
Scheduled task not configured yet
Please report issues at https://github.com/win-acme/win-acme

N: Create new certificate (simple for IIS)
M: Create new certificate (full options)
R: Run scheduled renewals (0 currently due)
A: Manage renewals (0 total)
O: More options...
Q: Quit

Please choose from the menu: n
```

- B. Select the number of the IoTstar website and apply a certificate for it.

```
Please select which website(s) should be scanned for host names. You may
input one or more site identifiers (comma separated) to filter by those
sites, or alternatively leave the input empty to scan *all* websites.

1: 88_IoTstar (1 binding)
7: 88_LIFF Tester (1 binding)

Site identifier(s) or <ENTER> to choose all: 1
```

- C. Select "3: Pick *all* bindings" to select all bindings of IoTstar website.

```
You may either choose to include all listed bindings as host names in your
certificate, or apply an additional filter. Different types of filters are
available.

1: Pick specific bindings from the list
2: Pick bindings based on a search pattern
3: Pick *all* bindings

How do you want to pick the bindings?: 3
```

- D. After the steps above, if all selections are correct, input "yes", the software will start the process to create the certificate. During the process, you can see the information and update time in the information list. After the process is completed, the software will automatically return to the main menu.

```
Continue with this selection? (y*/n) - yes
Target generated using plugin IIS: www.letstar.com
Authorize identifier www.letstar.com
Authorizing www.letstar.com using http-01 validation (SelfHosting)
Authorization result: valid
Requesting certificate [IIS] www.letstar.com, (any host)
Store with CertificateStore...
Installing certificate in the certificate store
Adding certificate [IIS] www.letstar.com, (any host) @ 2020/3/30 10:38:32 to store WebHosting
Installing with IIS...
Adding new https binding *:443:www.letstar.com
Committing 1 https binding changes to IIS
Adding Task Scheduler entry with the following settings
- Name win-acme renew (acme-v02.api.letsencrypt.org)
- Path C:\Program Files\win-acme.v2.1.6.768.x64.pluggable
- Command wacs.exe --renew --baseuri "https://acme-v02.api.letsencrypt.org/"
- Start at 09:00:00
- Time limit 02:00:00
Adding renewal for [IIS] www.letstar.com, (any host)
Next renewal scheduled at 2020/5/24 10:38:39

N: Create new certificate (simple for IIS)
M: Create new certificate (full options)
R: Run scheduled renewals (0 currently due)
A: Manage renewals (1 total)
O: More options...
Q: Quit

Please choose from the menu:
```

Please Note:

If you are using Let's Encrypt for the first time, you will be asked to provide an email address for the notification of the "Automatic Update Failure" event, input "yes" to agree the "Let's Encrypt Subscriber Agreement" for the proceeding.

```
Enter email(s) for notifications about problems and abuse (comma seperated): www.letstar.com
Terms of service: C:\ProgramData\win-acme\acme-v02.api.letsencrypt.org\LE-SA-v1.2-November-15-2017.pdf
Open in default application? (y/n*) - yes
Do you agree with the terms? (y*/n) - yes
```

※Maximum Application Frequency:


For the same Registered Domain: 20 times a week

For the same Domain Name: 5 times a week

For the same IP Address: 10 times every three hours

Due to the maximum application frequency includes the frequency of both creation and update operations, please do not launch the Application of certificate frequently to avoid exceeding the limitation.

(4) Launch "Internet Information Services (IIS) Administrator", select the IoTstar platform, and click on the "Binding" on the right side of the window. You will see an HTTPS type binding being automatically generated. Click "Restart" and then click on the HTTPS website to check if the IoTstar website can be executed successfully.



※Troubleshooting: Port 443 has been occupied

- A. Launch "Command Prompt" in the "Start Menu" of Windows. After the "Command Prompt" window is opened, input "**netstat -ano**" and press Enter.
- B. Find the item which Proto is "TCP", and the number after the ":" of the "Local Address" is 443; record its PID value. In this example, the following figure shows the PID is 4.

Proto	Local Address	Foreign Address	State	PID
TCP	0.0.0.0:80	0.0.0.0:0	LISTENING	4
TCP	0.0.0.0:88	0.0.0.0:0	LISTENING	4
TCP	0.0.0.0:135	0.0.0.0:0	LISTENING	1084
TCP	0.0.0.0:443	0.0.0.0:0	LISTENING	4
TCP	0.0.0.0:445	0.0.0.0:0	LISTENING	4
TCP	0.0.0.0:1230	0.0.0.0:0	LISTENING	13824
TCP	0.0.0.0:1231	0.0.0.0:0	LISTENING	13824
TCP	0.0.0.0:1232	0.0.0.0:0	LISTENING	13824
TCP	0.0.0.0:1233	0.0.0.0:0	LISTENING	13824
TCP	0.0.0.0:1234	0.0.0.0:0	LISTENING	13824
TCP	0.0.0.0:1235	0.0.0.0:0	LISTENING	13824
TCP	0.0.0.0:1433	0.0.0.0:0	LISTENING	6396
TCP	0.0.0.0:1883	0.0.0.0:0	LISTENING	4264
TCP	0.0.0.0:3306	0.0.0.0:0	LISTENING	4400
TCP	0.0.0.0:3389	0.0.0.0:0	LISTENING	1328

- C. In the "Command Prompt" window, input "**tasklist / FI "PID eq 4"** (please replace 4 with the PID value you got from the previous step). If the "Image Name" is "System" (shown as below); it indicates that the port 443 has been used properly by System. If not, it means the port is occupied by other program.

Image Name	PID	Session Name	Session#	Mem Usage
System	4	Services	0	6,556 K

- D. If the "Image Name" is not "System", it means the port 443 is occupied by other program. Please close the program which occupies port 443, and re-start the application of the SSL certificate again.

(If Skype have been installed on the Windows system, Port 443 may be occupied by Skype. You can open the Skype window, then click on the Tools menu and select Options. Click on the Advanced tab, and go to the Connection sub-tab. Untick or uncheck the checkbox for "Use port 80 and 443 as an alternative for additional incoming connections" option. Click on the Save button and then restart Skype to make the change effective.)